



- State-of-the-art, remote-controlled “separates” performance with the added benefit of balanced audio inputs for even greater audio qualify.
- Preamplifier section derived from the Coda 05x design, utilizing the Burr-Brown digitally-controlled precision analog attenuator. Component upgrades include PRP audio resistors, Multicap capacitors and high speed rectifiers for the preamp power supply
- Coda CSX Precision Bias Class A/AB amplifier design with discrete FET differential input stage, MOSFET voltage gain DC coupled to an ultra wideband bipolar output stage.
- Low overall feedback
- Separate tape monitor and processor loops
- Stereo subwoofer output
- Wideband, fully-regulated power supply with EMI and RFI line filtering
- Double-sided gold plated circuit
- All anodized chassis
- 10 year warranty / 5 year transferable
- Designed, manufactured and assembled in the USA

Rated Power:	V3:	400W/ch Class AB into 8Ω 800W/ch Class AB into 4Ω Class A ~8W @ 8Ω
	V2:	250W/ch Class AB into 8Ω 500W/ch Class AB into 4Ω Class A ~12W @ 8Ω
	V1:	150W/ch Class AB into 8Ω 300W/ch Class AB into 4Ω Class A ~18W @ 8Ω
Frequency Response:		DC to 100kHz @ -3dB
Distortion:		<.04% from 10Hz to 20kHz @ 400 Watts
Gain:		26dB
Maximum Current:		130 Amperes peak per channel
Noise:		-110dB
Input Impedance:		50kΩ balanced 1kΩ balanced
Output Impedance:		.04Ω from 20Hz to 20kHz
Power Supply:		3kVA toroidal power transformer. Dual independent rectification and 80,000uF of power supply filter capacitance
Dimension:		17" W x 14" D x 5.5" H
Weight :		55 lbs.