

marantz



AMP 20

12-Channel Power Amplifier

Reference 12-Channel 200-watt-per-channel power amplifier. Pair with AV 20 to create an elite-level home theatre. Marantz HDAM, Current Feedback Amplification, and balanced line level input.

- Detailed and immersive sound transforms your home theatre
- 200 watts per channel into 8Ω / 400 watts per channel into 4Ω
- 12 channels powers large home theatres
- Bi-amp mode drives high- and low-frequency sections of loudspeakers independently
- BTL Mode (Bridge mode) combines two channels into a single 400-watt per channel into 8Ω
- Perfect match for Marantz AV 20 preamplifier
- Balanced XLR input is ideal for reducing input noise
- Porthole with analogue meter measures output
- Soft side lights cast a warm glow on the front surface of the amplifier
- Elegant design matches rich, warm sound



The Most Musical Sound

AMP 20

Technical Specifications

Inputs/Outputs		
Audio	Main Amplifier In	Balanced & Unbalanced: 12ch (Exclusive use by a selector switch.)
Other	Speaker Terminal	SPKT-1+
	Number of Speaker Terminals	12
	Bi-Amp Drive / BTL Drive	Yes / Yes
	Level Meter	Yes
	Chassis	Copper Plated
Multi-Room		
RS232 Control		Yes
IR Flasher In		Yes
Marantz Remote Bus		Yes
DC Trigger Input / Output		1 / 1
Specifications		
Number of Power Amps		12
Power Output (8 ohm, 1 kHz, 0.05% 2ch Drive) Normal / BTL		200W / 400W
Power Output (4 ohm, 1 kHz, 0.7% 2ch Drive) Normal		400W
Power Output (8 ohm, 1 kHz, 0.7% 5ch Drive) Normal		200W
General		
Front Display		Level Meter
Auto Power Off		Yes
Metal Front Panel		Yes
Power Consumption		400W
Power Consumption, No-Sound		110W
Standby Consumption		0.2W
Maximum Dimensions (W × D × H)		442 × 442 × 191 mm
Weight		18.0 kg
What's in the Box		Main unit, quick start guide, AC cord, Amp control cable, Remote control cable, SP terminal wrench
EAN		747192145644



Design and specifications are subject to change by Marantz without notice.

www.marantz.com

